

Printed pages:4

EIC501

(Following paper code and roll No. to be filled in your answer book)

Paper code: 132502

Roll No.

--	--	--	--	--	--	--	--	--	--

B TECH
(SEM V) THEORY EXAMINATION 2014-15
CONTROL SYSTEM-I

TIME: 3 Hours

Total Marks: 100

Note: Attempt questions from each Section as per instructions.

SECTION-A

1. Attempt ALL parts. 2*10=20

- a. Classify control Systems and give the merits and demerits of open loop control system & closed loop control system.
- b. For the forward path, TF given by

$$G(s) = \frac{20(s+2)}{s(s+3)(s+4)}$$

Find Error coefficients.

- c. Explain the Incremental Encoder?
- d. Find the breakaway points of
$$G(s)H(s) = \frac{K}{s(s+4)(s^2+4s+20)}$$
- e. Find the Gain margin of $G(s) = \frac{80}{s(s+2)(s+20)}$
- f. Under damped systems are most preferred system. Explain why?
- g. How transfer function can be obtained from state equations. Explain.
- h. A system has a transfer function $\frac{C}{R} = \frac{20}{s+10}$. Determine its Unit Impulse Response.
- i. Explain Mason Gain Formula briefly.
- j. Find the phase system $G(s)H(s) = \frac{e^{-0.2s}}{s(s+1)}$ for $\omega=5$.

4. Attempt any three parts

10*3=30

- a. Draw the Bode Plot for the transfer function
 $G(S) = 36 (1+0.2 s) / s^2(1+0.05s)(1+0.01s)$
From the bode plot determine
- Phase crossover frequency
 - Gain crossover frequency
 - Gain Margin
 - Phase Margin
- b. Determine the type and order of the unity feedback control systems whose open-loop transfer functions are
- $G(S) = K / S(S^2+4S+200)$

Find also the static error coefficients and the errors for unit step and unit ramp inputs.

- c. A Second –order system has overshoot of 50% and period of oscillation 0.2 s in step response .determine resonant peak, resonant frequency and bandwidth.
- d. The closed –loop transfer function of certain second – order unity feedback control systems are given below. Determine the type of damping in the systems:
- $C(S)/R(S) = 8/S^2+3S+8$
 - $C(S)/R(S) = 4/S^2+16$